

Sub 317 1. (Original): A digital data modulator, comprising:

- a source of a digital data signal;
- an encoder, for encoding the digital data using a variable pulse width code;
- a pulse signal generator, generating respective pulses representing edges of the encoded digital data signal; and
- a carrier signal generator, for generating a carrier signal having carrier pulses corresponding to the respective pulses.

2. (Original): The modulator of claim 1 wherein the variable pulse width codes is a variable aperture code.

AI Cont 3. (Original): The modulator of claim 1 wherein:

the encoder generates an encoded digital data signal having leading edges and trailing edges;

the pulse signal generator generates positive pulses in response to a first edge in the digital data signal and negative pulses in response to a different second edge in the digital data signal; and

the carrier signal generator generates a carrier pulse having a first phase in response to a positive pulse and having a second phase in response to a negative pulse.

4. (Original): The modulator of claim 3 wherein the first phase is substantially 180 degrees out of phase with the second phase;

said first edge is a leading edge; and

said second edge is a trailing edge.

5. (Currently amended): ~~The modulator of claim 1~~ A digital data modulator, comprising:
a source of a digital data signal;
an encoder, for encoding the digital data using a variable pulse width code;
a pulse signal generator, generating respective pulses representing edges of the encoded
digital data signal; and
a carrier signal generator, for generating a carrier signal having carrier pulses
corresponding to the respective pulses;

wherein the pulse signal generator comprises:

a differentiator, coupled to the encoder; and

a level detector, coupled to the differentiator.

6. (Currently amended): ~~The modulator of claim 1~~ A digital data modulator, comprising:
a source of a digital data signal;
an encoder, for encoding the digital data using a variable pulse width code;
a pulse signal generator, generating respective pulses representing edges of the encoded
digital data signal; and
a carrier signal generator, for generating a carrier signal having carrier pulses
corresponding to the respective pulses;

wherein the carrier signal generator comprises:

a carrier oscillator; and

a mixer, having a first input terminal coupled to the pulse signal generator and a second input terminal coupled to the carrier oscillator.

7. (Original): The modulator of claim 6 further comprising a bandpass filter coupled to an output terminal of the mixer.

8. (Original): A digital data demodulator, comprising:

a source of a modulated signal, having carrier pulses spaced relative to each other to represent a variable pulse width encoded digital data signal;

A1
cont
a detector for generating a variable pulse width encoded signal in response to received carrier pulses;

a decoder for decoding the variable pulse width encoded signal to generate the digital data signal.

9. (Original): The demodulator of claim 8 wherein the variable pulse width code is a variable aperture code.

10. (Original): The demodulator of claim 8 wherein the carrier pulses have one of a first phase and a second phase.

11. (Original): The demodulator of claim 10 wherein the first phase is substantially 180 degrees out of phase with the second phase.

12. (Currently amended): ~~The demodulator of claim 8~~ A digital data demodulator,
comprising:

a source of a modulated signal, having carrier pulses spaced relative to each other to
represent a variable pulse width encoded digital data signal;

a detector for generating a variable pulse width encoded signal in response to received
carrier pulses;

a decoder for decoding the variable pulse width encoded signal to generate the digital data
signal;

further comprising, coupled between the modulated signal source and the detector:

a bandpass filter;

an integrator; and

a limiting amplifier.

13. (Currently amended): ~~The demodulator of claim 8~~ A digital data demodulator,
comprising:

a source of a modulated signal, having carrier pulses spaced relative to each other to
represent a variable pulse width encoded digital data signal;

a detector for generating a variable pulse width encoded signal in response to received
carrier pulses;

a decoder for decoding the variable pulse width encoded signal to generate the digital data
signal;

further comprising:

a windowing timer, coupled to the detector; for generating a windowing signal in the
temporal neighborhood when a carrier pulse is expected; and wherein:

the detector is enabled by the windowing signal.

14. (Original): A digital data modulation method comprising the steps of:

providing a source of a digital data signal;

encoding the digital data using a variable pulse width code;

generating respective pulses representing edges of the encoded digital data signal; and

generating a carrier signal having carrier pulses corresponding to the respective pulses.

15. (Original): A digital data demodulation method comprising the steps of:

providing a source of a modulated signal, having carrier pulses spaced relative to each other to represent a variable pulse width encoded digital data signal;

generating a variable pulse width encoded signal in response to received carrier pulses;

decoding the variable pulse width encoded signal to generate the digital data signal.

AI
concl